



+ [View More](#)

PRODUCT NUMBER: 1011170

Viking V3 Multiple-Position Earmuff

Overview

Reference Number
1011170

Product Type
Hearing Protection

Range
Earmuffs

Line
Noise Blocking Earmuffs

Brand
Howard Leight by Sperian

Brand formerly known as
BILSOM

- Industry**
- Army - Defence
 - ATEX environment
 - Automotive and Part Manufacturer
 - Aviation
 - Building and Construction
 - Catering
 - Chemical Industries
 - Energy or Electricity
 - Fire Protection brigades
 - Fishing
 - Food Industries
 - Foundry
 - Glass Industries
 - Green Spaces
 - Homeland defense
 - Industrial Cleaning
 - Iron and steel industry
 - Logistics
 - Maintenance
 - Medical and Pharmaceutical
 - Metal steel
 - Minning and Quarrying
 - Offshore
 - Paper Industries
 - Petro-chemical
 - Printing Industries
 - Services
 - Telecoms
 - Textile Industries
 - Transportation
 - Utilities
 - Water treatment
 - Welding
 - Wood Industries
 - Laboratory
 - Ship Building
 - Industry
 - Administration

● Agriculture

Product Use

Noise Blocking Earmuff

Features & Benefits

Feature

Multiple-position headband allows wearer to select position over-the-head, behind-the-head or under-the-chin Air Flow Control™ technology, delivering optimal attenuation across all frequencies, without increasing earcup size or weight Inner-ventilated headband minimizes pressure on the head, breathes easier in warm/humid climates Alternative to cap-mounted earmuffs - wear with hard hats, face shields, respirators and other PPE Non-deforming outer headband withstands rough treatment in the toughest workplaces Snap-in ear cushions make replacement quick and easy Includes headband strap for better positioning when worn behind-the-head or under-the-chin Dielectric construction suitable for all workplaces, especially electrical environments

Benefit

The Viking™ series multiple-position earmuff gives workers flexibility to wear their earmuffs over-the-head, behind-the-head and under-the-chin. Viking earmuffs can be worn with other PPE, including hard hats, visors, face shields, respirators and welding shields. Plus, Viking's robust non-deforming dielectric construction withstands use and abuse, while protecting your workers in electrical environments. NOW FEATURING AIR FLOW CONTROL™ TECHNOLOGY

Technical Description

SNR (dB)

32

H (dB)

33

M (dB)

30

L (dB)

24

Attenuation Data

	63	125	250	500	1000	2000	4000	8000
Frequency (Hz) Frequenz (Hz) Fréquence (Hz)								
Mean Attenuation (dB) Mittlere Dämmung (dB) Atténuation moyenne (dB)	16.3	20.0	24.6	29.8	36.0	33.9	38.3	37.3
Standard Deviation (dB) Standardabweichung (dB) Déviation standard (dB)	2.9	2.3	1.6	2.1	2.8	2.9	2.3	4.0
Assumed Protection	13.4	17.7	23.0	27.7	33.2	31.0	36.0	33.3

(dB) Angenommener
(dB) Protection
supposée (dB)

Earmuff Construction

Plastic [or Dielectric]

Other Material

PP webbing, POM, LDPE, PA, EPDM, ABS, PUR-E, PP, PVC

Dielectric

Yes

Color

Black and Silver

Batteries Needed

None

Weight (grs)

248

Design Patents

Air Flow Control™

Headband Style

Multiple-Position

Sound Amplification

No

AM/FM Radio

No

Automatic Shut-Off Function

No


Audio Input Jack

No

Hi-Visibility

No

Certifications

 E.C. Declaration of Conformity

EC Category PPE

2


Quality Assurance

ISO 9001 / 2000

EC Certificate Number

1487


EC Attestation


 EC Attestation

EC Attestation Number

060554

Literature & Documents

 **E.C. Declaration of Conformity**

 **PIC SKU - Pictures**

<http://www.honeywellsafety.com/assets/0/324/500/51887/a138df44f53e4d5fae014a81aa6869c6.jpg>

Photos & Images

We're sorry, there are no images available at this time.

Maintenance

Life Cycle

Cushions should be replaced periodically to retain maximum attenuation. Use the following as a guideline for replacement of ear cushions and insert foam. General use and wear - Ear cushions and foam inserts should be replaced at least every 6 months. Heavy use or wear in humid/extreme climates - Ear cushions and foam inserts should be replaced at least every 3 months. Cracking or leakage is visible - replace ear cushions and foam inserts immediately.

Storage Information

When not in use, the earmuffs should be stored in a clean dry container or locker. Do not use solvents or petroleum-based products. Do not immerse the earmuffs in water.

Care Instructions

Earmuffs are an important safety product and should be inspected regularly. Its use, care and maintenance are critical to its effective performance. Earmuffs and in particular ear cushions may deteriorate with use and should be examined at frequent intervals for cracking and leakage. If the ear cushions become hard, damaged or deteriorated, they should be replaced promptly using recommended Hygiene Kits. Earmuffs should be maintained by regular cleaning. Use a mild disinfectant solution. A gentle wipe is all that is required.

Parts & Accessories

Accessories

Hygiene Kit - Packed in a plastic bag, including two ear cushions and two liners. Ref. # 1010978 for V3

Beltclip - For carrying purpose. Old Ref. # 1000252 New Ref. # 1016730 Cool II Pads - Sweat absorbing pads. Ref. # 1000365 5-pair, Ref. # 1000364 100-pair

Optisorb - cotton sleeve slides over earcup. Ref. # 3302101

Polar Hood - Ref. # 1016870 Lg/XLg; Ref. # 1016871 Sm/Med

Packaging

EAN Code

7312550111703

Honeywell

[View other region sites](#)

© 2011 Honeywell International Inc.